



APPLICATION Note

TELECOM SOLUTIONS FOR THE 21ST CENTURY

RC-2A

Using the RC-2A with a 4x4 Keypad

May 3, 2001

Using the RC-2A with a 4x4 Keypad for Extreme Security Applications

IMPORTANT: This document is to be used in conjunction with the **RC-2A Technical Practice (Fax Back Document 160)**.

A. Legacy Programming (JP1 in place)

The **RC-2A** contains (3) rotary access code switches. Using a small flat blade screwdriver, rotate the white arrow on each switch to the desired access code setting.

1	2	3	A
4	5	6	B
7	8	9	C
*	0	#	D

Touch Tones	Switch Setting
0-9	0-9
*	B
#	C
A	D
B	E
C	F

B. Alternative Programming (JP1 removed)

The **RC-2A** contains (3) rotary access code switches (see diagram below). Using a small flat blade screwdriver, rotate the white arrow on each switch to the desired access code setting.

1	2	3	A
4	5	6	B
7	8	9	C
*	0	#	D

Touch Tones	Switch Setting
0-9	0-9
*	B
#	C
A	D
B	E
Ignore	F

Product Support Line...715.386.8666

Fax Back Line...715.386.4345

Due to the dynamic nature of the product design, the information contained in this document is subject to change without notice. Viking Electronics, and its affiliates and/or subsidiaries assume no responsibility for errors and omissions contained in this information. Revisions of this document or new editions of it may be issued to incorporate such changes.